

<<< SCA Adapter ID Setting >>>

SCSI ID Number	Jumper Settings
0	
1	
2	
3	
4	
5	
6	
7	
8	
9	
10	
11	
12	
13	
14	
15	

ID0: SCSI ID # bit 0
 ID1: SCSI ID # bit 1
 ID2: SCSI ID # bit 2
 ID3: SCSI ID # bit 3
 MTR: RMT-Start
 DLY: Start delay
 SYN: Synchronous
 LED: LED

R80A01,A02,A04 CN5 PIN ASSIGNMENT				
		PIN	PIN	
ACTIVE LED OUT	LED	15	16	
SPINDLE SYNCHRONOUS	SYN	13	14	
DELAY START	DLY	11	12	
REMOTE START	MTR	9	10	
ID SELECT	ID3	7	8	
ID SELECT	ID2	5	6	
ID SELECT	ID1	3	4	
ID SELECT	ID0	1	2	
	ID0	ID1	ID2	ID3
0	OPEN	OPEN	OPEN	OPEN
1	SHORT	OPEN	OPEN	OPEN
2	OPEN	SHORT	OPEN	OPEN
3	SHORT	SHORT	OPEN	OPEN
4	OPEN	OPEN	SHORT	OPEN
5	SHORT	OPEN	SHORT	OPEN
6	OPEN	SHORT	SHORT	OPEN
7	SHORT	SHORT	SHORT	OPEN
8	OPEN	OPEN	OPEN	SHORT
9	SHORT	OPEN	OPEN	SHORT
10	OPEN	SHORT	OPEN	SHORT
11	SHORT	SHORT	OPEN	SHORT
12	OPEN	OPEN	SHORT	SHORT
13	SHORT	OPEN	SHORT	SHORT
14	OPEN	SHORT	SHORT	SHORT
15	SHORT	SHORT	SHORT	SHORT